



## PROBLEM:

The input to the C-to-D converter in the figure below is

$$x(t) = 3 + 2 \cos(6000\pi t - \pi/4) + 11 \cos(12000\pi t - \pi/3)$$

The system function for the LTI system is

$$H(z) = \frac{1}{4}(1 - z^{-4})$$

If  $f_s = 8000$  samples/second, determine an expression for  $y(t)$ , the output of the D-to-C converter.

